

FT1D SOTA Trail Card

Volume VOL → C Hold Set	Mute VOL Press	Lock PWR PWR Press	Modes Dx Press
Squelch F → MONI → C → PTT Hold Set Save			DN (Auto) DN (Narrow) VW (Wide) FM (Analog)
TX Power F → TX PWR → C → PTT L1 ▶ L2 ▶ L3 ▶ HI			
A/B Bands A/B → A/B → A/B Toggle TX on A/B Hold ▶ Mono		Misc [L1 = 0.1 w] [L2 = 1.0 w] [L3 = 2.5 w] [HI = 5.0 w]	
VFO/Bank Scan F → SCAN → PTT Start Scan Exit			SIMPLEX CH 00 = 146.520 17 = 146.580 20 = 446.000
Battery Voltage A/B → F → A/B Hold ▶ Mono Display Voltage			Direct Recall # → ENT Memory Number

KX6A

Store VFO to Memory V/M → C → F → C → F MR ▶ VFO Tune Hold Select Hold
Repeater Shift / Simplex DISP → C → ENT → C → ENT Hold [8 CONFIG] [15 RPT SHIFT]
CTCSS Tone On/Off DISP → C → ENT → C → ENT Hold [4 SIGNALING] [11 SQL TYPE]
CTCSS Tone Frequency DISP → C → ENT → C → ENT Hold [4 SIGNALING] [12 TONE SQL]
Memory Name DISP → C → ENT → C → ENT Hold [3 MEMORY] [3 MEMORY NAME]
Memory Bank BAND → F → BAND → C → BAND MR ▶ Bank Set Save

MWGBLOG.LINK/FT1D_SOTA

FT1D SOTA Trail Card

Activate APRS - Menu [9 APRS]

- Select B-band for TX, set to 144.390 MHz
- Turn on GPS [20 GPS POWER]
- Select GPS [24 MY POSITION]
- Choose Beacon Options [14, 15, 16, 27]

Manual Beacon **F** → **9** BCON TX

APRS Message

F → **0** → **0** / **C** → **ENT**
APRS MESSAGE LIST REUSE CALLSIGN/MSG

GM → Enter Call / SSID → Enter Message /

A/B → **V/M** → **ENT** || **V/M**
Select Fixed Text Hold to Send Delete MSG

APRS SOTA

SOTA · W6/CT-001 14.285 SSB KX6A active now
CALLSIGN Summit / Freq / Mode / Callsign / Comment

GPS Position / Info

DISP → **C** → **ENT** → **C** → **ENT**
Hold [1 DISPLAY] [1 GPS POWER]

KX6A

Save GPS Position

DISP → **C** → **ENT** → **C** → **ENT**
Hold [9 APRS] [24 MY POSITION]

VFO / Bands / AM / FM

V/M **C** **BAND** **F** → **BAND**
MR ▶ VFO Tune Band Up Band Down

Weather Band

A/B → **F** → **3** → **BAND** **3**
A-band P. RCVR Select WX P. RCVR To Exit

Beacon Shortcut

F → **0** **BAND** **Icons**
S.LIST-APRS APRS MESSAGE LIST Man ▶ Auto AUTO SMART

Text Editing

A/B
CLR (to end)
 INSERT (chr)
 CLRALL (all)
 DELETE (chr)
V/M

Text Entry

ENT **F** **C** **PTT**
Enter Back Select Save

Band Scope

V/M **C** **BAND**
MR ▶ VFO Tune Hold

MWGBLOG.LINK/FT1D_SOTA